

Apr.1.2024 Copyright 2024 HIROSE ELECTRIC CO., LTD. All Rights Reserved.
In case of consideration for using Automotive equipment / device which demand high reliability, kindly contact our sales window correspondents.

1		2		3		4	
A						A	
B						B	
C						C	
D						D	
E						E	
F						F	

250 ± 8

1

3 Gray

2

NOTE 1 Do not apply any excessive stress to the cable assembly position.

【 DIMENSIONS OF CONNECTOR 】

5 ± 0.4

2.0

HR5

1.85 ± 0.2

【 PRECAUTIONS FOR HANDLING 】

- ◆ Connector insertion and extraction
 - a. Connector shall be extracted vertically by specialised extraction JIG.
Part No. : U.FL-LP-N-2CCL Code: CL331-0494-5)
Never hold the cable when extracting the cable because it damages the connector.
 - b. Insert the connector as perpendicularly to the mating surface as possible by aligning the mating axes of both connectors. Do not excessively slant the connectors when inserting.
- ◆ Allowable loads on the cable after the connectors are mated.
The figures below shot the maximum allowable loads on the cable. Do not apply loads exceeding these values to the cable.

U.FL-LP-N-2

U.FL-LP-088HF

U.FL-R-SMT-1

2	U.FL-LP-088HF(06)	CL331-0560-8-06	3	RF-MF50141(Gray)	NISSEI ELECTRIC CO., LTD.
1	HRM-200-088PBN(40)	CL323-0800-5-40			
NO.	PART NO.	CODE NO.	NO.	PART NO.	MANUFACTURER

UNITS mm		SCALE FREE	COUNT 	DESCRIPTION OF REVISIONS	DESIGNED	CHECKED	DATE

HIROSE
ELECTRIC
CO., LTD.

APPROVED : TO. KATAYAMA 20190610

CHECKED : TO. KATAYAMA 20190610

DESIGNED : NK. OOSAWA 20190607

DRAWN : ST. KISHI 20190606

DRAWING NO. EDC-388864-01-00

PART NO. HRMP-UFLHF6-088N1T-A250RS

CODE NO. CL321-1716-0-01

1/1

FORM HC0011-5-51

2

3

4