

Apr.1.2024 Copyright 2024 HIROSE ELECTRIC CO., LTD. All Rights Reserved.
In case of consideration for using Automotive equipment / device which demand high reliability, kindly contact our sales window correspondents.

1

2

3

4

【 ASSEMBLE TOOL 】

APPLICABLE OUTER CONDUCTOR CRIMPING TOOL : HT103/MRF01-J-178

TOOL FOR PRESS FITTING OF DISK

: MMCX-LP/PR-MP

A

B

C

D

E

Attached 7

4 ± 0.2

2

6 Attached

11 ± 0.4

7 ± 0.3

5.25 ± 0.2

2.8 ± 0.1

1

5

3

4

(φ 0.9)

(φ 1.9)

HRS DRAWING FOR REFERENCE

【 Usage precautions of MMCX(AR) 】

Insertion or extraction a plug of MMCX(AR) as perpendicularly as possible with aligning the plug with a receptacle.

When aligned insertion or extraction is not performed, it would damage or deform an outer conductor part.

Top of outer conductor

RoHS COMPLIANT

4	PHOSPHOR BRONZE	GOLD PLATING			
3	PTFE		7	BRASS	GOLD PLATING
2	BRASS	GOLD PLATING	6	COPPER	GOLD PLATING
1	BRASS	GOLD PLATING	5	BERYLLIUM COPPER	GOLD PLATING
NO.	MATERIAL	FINISH . REMARKS	NO.	MATERIAL	FINISH . REMARKS

UNITS
mm

SCALE
10 : 1

COUNT

DESCRIPTION OF REVISIONS

DESIGNED

CHECKED

DATE

HRS

HIROSE ELECTRIC CO., LTD.

APPROVED : TO. KATAYAMA

CHECKED : TO. KATAYAMA

DESIGNED : NK. OOSAWA

DRAWN : NK. OOSAWA

17. 09. 08

17. 09. 08

17. 09. 08

17. 09. 08

DRAWING NO.

PART NO.

CODE NO.

EDC-334203-00-00

MMCX(AR)-LP-FHSB

CL339-0035-9-00

1/1

FORM HC0011-5-51

2

3

4