



Feb.1.2024 Copyright 2024 HIROSE ELECTRIC CO., LTD. All Rights Reserved.
In case of consideration for using Automotive equipment / device which demand high reliability, kindly contact our sales window correspondents.












1 FIGURE OF INSERTION

HORIZONTALLY ○



DIAGONAL ×





HRS DRAWING FOR REFERENCE

NOTE 1 AVOID ANGLED INSERTION OF CRIMP CONTACT(DF57-****SCF) TO MAINTAIN PERFORMANCE RELIABILITY.

	CODE No.	PART No.	NUMBER OF CONTACTS	A	B	C	D	D
	CL666-0100-6-08	DF57H-2S-1.2C(08)	2	1.2	3.5	2.98	2.6	3.15
	CL666-0012-0-08	DF57H-3S-1.2C(08)	3	2.4	4.7	4.18	3.8	4.35
1	CL666-0101-9-08	DF57H-4S-1.2C(08)	4	3.6	5.9	5.38	5.0	5.55
	CL666-0102-1-08	DF57H-5S-1.2C(08)	5	4.8	7.1	6.58	6.2	6.75
1	CL666-0103-4-08	DF57H-6S-1.2C(08)	6	6.0	8.3	7.78	7.4	7.95

部番	材質	処理，備考
1	LCP	UL94V-0, NATURAL(BEIGE)

UNITS mm | SCALE 20：1

△の数	訂正記事	設計	検図	年月日
2	DIS-H-008103	TS. KUMAZAWA	HK. UMEHARA	13. 08. 19

HIROSE ELECTRIC CO., LTD.

承認	KI. AKIYAMA	12. 11. 21
検図	HK. UMEHARA	12. 11. 21
設計	TS. KUMAZAWA	12. 11. 21
製図	TS. KUMAZAWA	12. 11. 21


図番：EDC3-349275-01
製品名：DF57H-*S-1.2C(08)
製品コード：CL666-
1 1/2

Feb.1.2024 Copyright 2024 HIROSE ELECTRIC CO., LTD. All Rights Reserved.
In case of consideration for using Automotive equipment / device which demand high reliability, kindly contact our sales window correspondents.


DF57 Series Mating / Unmating Operation Instruction

Mating


①By positioning the convexity of the socket sides to the header concavity, align the centers of the socket and the header in pitch direction.



②Slightly press the socket down at cable side to tilted angle.




③Press down at the lever side with stabilizing the cable side to insert. Mating completes.




HRS DRAWING FOR REFERENCE

Unmating


①Hook the lever with finger nail.



②Lift up to the upper difrection and friction lock is released.



③Lift up to the upper direction and positive lock is released. Removal completes.



DRAWING NO.	EDC3-349275-01
PART NO.	DF57H-*S-1.2C(08)
CODE NO.	CL666-