


Mar.1.2024 Copyright 2024 HIROSE ELECTRIC CO., LTD. All Rights Reserved.
In case of consideration for using Automotive equipment / device which demand high reliability, kindly contact our sales window correspondents.


HRS DRAWING FOR REFERENCE




Isometric Diagram












A-A





Assembly Diagram (2:1)



Notes
1. Please attach Keigland E2KD 1620 of SANKEI CO., LTD to this product before use.
2. The contact will be sent with Ref. No. ⑤ press-fitted to Ref. No. ④.
3. Rotation examples of ref no.① and ③ are shown.
3. 4. Recommended Crimping Tool: JIS-C-9711 IZUMI CO., LTD REC-Li150.
4 1 5. Make sure that the Keigland shell is tightened to the end of the screw. The recommended tightening torque is 2 to 3 N・m. Furthermore, to prevent loosening, it is recommended that thread-locking fluid be used.
2. 6. This product is UL certified. (File E481344)
3. 7. Dropouts and the like may occur, so when mated,
Please do not leave with the mating guide of the opposite side and the arrow marks out of alignment.

WARNING . This product is not hot pluggable.

NO.	MATERIAL	FINISH , REMARKS	NO.	MATERIAL	FINISH , REMARKS
3	PBT	(Black) UL94V-0	6	PBT	(Black) UL94V-0
2	Fluorosilicone rubber	(Black)	5	PBT	(Black) UL94V-0
1	PBT	(Black) UL94V-0	4	Copper	Silver plating 3μm

UNITS	SCALE		COUNT	DESCRIPTION OF REVISIONS	DESIGNED	CHECKED	DATE
mm	1 : 1	4	1	DIS-C-00011653	TY. TAKAHASHI	EJ. KUNII	20220616

HRS HIROSE ELECTRIC CO., LTD.

APPROVED	EJ. KUNII	20160225	DRAWING NO. EDC-119508-00-00
CHECKED	EJ. KUNII	20160225	PART NO. EM30M-WBP-1PCA-K
DESIGNED	TY. TAKAHASHI	20160225	
DRAWN	TY. TAKAHASHI	20160225	CODE NO. CL0138-0074-0-00

4 1/1