



Feb.1.2024 Copyright 2024 HIROSE ELECTRIC CO., LTD. All Rights Reserved.
In case of consideration for using Automotive equipment / device which demand high reliability, kindly contact our sales window correspondents.


HRS DRAWING FOR REFERENCE











NOTE1. PER PACK : 100 PIECES
2. REFER TO THE DF59 SERIES MATING/UNMATING OPERATION INSTRUCTION MANUAL(ETAD-H0496) FOR THE OPERATING OF THE PRODUCT.
△1 3. UL(FILE NO. E52653), C-UL(FILE NO. E52653) APPROVED PRODUCT.

NO.	MATERIAL	FINISH , REMARKS
1	PBT	UL94V-0, NATURAL(WHITE)

UNITS	SCALE		COUNT	DESCRIPTION OF REVISIONS	DESIGNED	CHECKED	DATE
mm	5 : 1	△1	1	DIS-H-006828	MI. SAKIMURA	HK. UMEHARA	12. 04. 20

HIROSE ELECTRIC CO., LTD.

APPROVED	KI. AKIYAMA	11. 03. 25
CHECKED	OM. MIYAMOTO	11. 03. 25
DESIGNED	KT. ISHII	11. 03. 25
DRAWN	KT. ISHII	11. 03. 25


DRAWING NO.	EDC3-331128-01
PART NO.	DF59-4P-2C
CODE NO.	CL667-0013-0-00

△1 1/2


Operation Procedures for Crimp Socket

〖Mating〗

1. By positioning the convexity of the crimp socket sides to the receptacle concavity, align the centers of the crimp socket and the receptacle in pitch direction.




2. Keep pressing down at the cable side and also apply force to the lever side to mate.
(If the cable side floats before mating is finished, the lock may not work.)




〖Unmating〗

1. Hook the lever with finger and lift up to the upper direction for unlock.
Note) When lifting up the lever, do not apply downward force to the cable side of the crimp socket. This could damage the connector.



Make sure to use the lever for removal oeration.
If the cable is pull for removal, it could break the cable or damage the connector.



HRS DRAWING FOR REFERENCE

HRS	図番：	EDC3-331128-01
	製品名：	DF59-4P-2C
	製品コード	CL667-0013-0-00

Feb.1.2024 Copyright 2024 HIROSE ELECTRIC CO., LTD. All Rights Reserved.
In case of consideration for using Automotive equipment / device which demand high reliability, kindly contact our sales window correspondents.