

Notes 1 Rotation example of Ref. No.① and ⑤ are shown.
2 The tighteninig torque of Ref. No.⑤ : 2 to 3 N・m.
3 The tighteninig torque of Ref. No.⑧ : 0.2 to 0.3 N・m.
Across flats hexagon head of Ref. No.⑧:1.27
Apply Loctite 243 HENKEL JAPAN or equivalent to the threaded portion of Ref. No.⑧ in order to prevent loosening.
4 The tighteninig torque of Ref. No.⑦ : 0.12 to 0.15 N・m.
Apply Loctite 243 HENKEL JAPAN or equivalent to the threaded portion of Ref. No.⑦ in order to prevent loosening.
5 The cable pull and twisting strength and other characteristics may differ, depending on the cable structure, please confirm before the use.

NO.	MATERIAL	FINISH , REMARKS	NO.	MATERIAL	FINISH , REMARKS
4	Polyphenylene sulfide	(Black)	8	Steel	Nickel plating Hexagon socket set screws M2.6×0.45×2
3	Polyphenylene sulfide	(Black)	7	Brass	Nickel plating Slotted head screw M2×0.4×8
2	Copper alloy	Silver plating 5μm min.	6	Zinc alloy	Matte finish nickel plated
1	Zinc alloy	Matte finish nickel plated	5	Zinc alloy	Matte finish nickel plated

UNITS	SCALE	COUNT	DESCRIPTION OF REVISIONS	DESIGNED	CHECKED	DATE
mm	2 : 1	1	DIS-C-00016538	TY. SUZUKI	HY. KOBAYASHI	20240201

HIROSE ELECTRIC CO., LTD.

APPROVED	TP. KOMATSU	20230612
CHECKED	HY. KOBAYASHI	20230612
DESIGNED	HT. ZENBA	20230609
DRAWN	KR. SUZUKI	20230607

DRAWING NO.	EDC-006967-81-00
PART NO.	RM12BJB-7S(81)
CODE NO.	CL0109-0643-6-81

1/1