Rating Power W temperature range Characteristic impedance 75 Ω(Applicable	X X X X X X X X X X
Rating Power W Characteristic impedance 1.5 Dia	QT A X X X X X X X X X
Power W Characteristic impedance 75 Ω(impedance 250 V DC. Withstanding voltage 300 V AC for 1 min. current leakage 2 mA Max. No flashover or breakdown. Withstanding voltage Wish and with the product of 1.5 GHz. Wathstanding voltage Wish and the product of 1.5 GHz. Wathstanding voltage Wish and the product of 1.5 GHz. Wathstanding voltage Wish and the product of 1.5 GHz. Wathstanding voltage Wish and the product of 1.5 GHz. Wathstanding to display the product of 1.5 GHz.	A
Peculiarity Applicable cable 1.5 Dia SPECIFICATIONS ITEM TEST METHOD REQUIREMENTS CONSTRUCTION General examination Visually and by measuring instrument. According to drawing. ELECTRICAL CHARACTERISTICS Insulation resistance 250 V DC. 500 MΩ Min. Withstanding voltage 300 V AC for 1 min. current leakage 2 mA Max. No flashover or breakdown. VSWR 1.25 Max. (RL.19dBMi wave ratio Frequency 0 to 1.5 GHz. VSWR 1.25 Max. (RL.19dBMi wave ratio Frequency 1.5 to 3 GHz. VSWR 1.5 Max. (RL.14dBMi MECHANICAL CHARACTERISTICS Cable clamp strength Using a pulling tester, pull the cable axially at a rate (Against cable pull) Of 10 mm/min. and record the strength at which 14.7 N Min.	A
Peculiarity	QT A' X X X X X X X X X
SPECIFICATIONS ITEM TEST METHOD REQUIREMENTS CONSTRUCTION General examination Visually and by measuring instrument. According to drawing. ELECTRICAL CHARACTERISTICS Insulation resistance 250 V DC. 500 MΩ Min. Withstanding voltage 300 V AC for 1 min. current leakage 2 mA Max. No flashover or breakdown. Voltage standing Frequency 0 to 1.5 GHz. VSWR 1.25 Max. (RL.19dBMi wave ratio Frequency 1.5 to 3 GHz. VSWR 1.5 Max. (RL.14dBMi MECHANICAL CHARACTERISTICS Cable clamp strength (Against cable pull) Using a pulling tester, pull the cable axially at a rate (Against cable pull) of 10 mm/min. and record the strength at which	QT A' X X X X X X X X X
SPECIFICATIONS ITEM TEST METHOD REQUIREMENTS	X X X X X X X X X X
TEM TEST METHOD REQUIREMENTS	X X X X X X X X X X
CONSTRUCTION General examination Visually and by measuring instrument. According to drawing. ELECTRICAL CHARACTERISTICS Insulation resistance 250 V DC. 500 MΩ Min. Withstanding voltage 300 V AC for 1 min. current leakage 2 mA Max. No flashover or breakdown. Voltage standing wave ratio Frequency 0 to 1.5 GHz. VSWR 1.25 Max. (RL.19dBMin. WECHANICAL CHARACTERISTICS VSWR 1.5 Max. (RL.14dBMin. Cable clamp strength (Against cable pull) Using a pulling tester, pull the cable axially at a rate (Against cable pull) 14.7 N Min.	X X X X X X X X X X
General examination Visually and by measuring instrument. According to drawing.	X X X X X X X X X X
ELECTRICAL CHARACTERISTICS Insulation resistance 250 V DC. 500 MΩ Min. Withstanding voltage 300 V AC for 1 min. current leakage 2 mA Max. No flashover or breakdown. Voltage standing Frequency 0 to 1.5 GHz. VSWR 1.25 Max. (RL.19dBMi wave ratio Frequency 1.5 to 3 GHz. VSWR 1.5 Max. (RL.14dBMi MECHANICAL CHARACTERISTICS Cable clamp strength Using a pulling tester, pull the cable axially at a rate (Against cable pull) of 10 mm/min. and record the strength at which	X X X X X X X X X X
Insulation resistance 250 V DC. Withstanding voltage 300 V AC for 1 min. current leakage 2 mA Max. No flashover or breakdown. Voltage standing prequency 0 to 1.5 GHz. Frequency 1.5 to 3 GHz. WSWR 1.25 Max. (RL.19dBMink VSWR 1.5 Max.) WSWR 1.5 Max. (RL.14dBMink VSWR 1.5 Max.)	X X X in)
Withstanding voltage 300 V AC for 1 min. current leakage 2 mA Max. No flashover or breakdown. Voltage standing Frequency 0 to 1.5 GHz. Frequency 1.5 to 3 GHz. VSWR 1.25 Max. (RL.19dBMi VSWR 1.5 Max.) MECHANICAL CHARACTERISTICS Cable clamp strength (Against cable pull) Using a pulling tester, pull the cable axially at a rate (Against cable pull)	X X X in)
Voltage standing Frequency 0 to 1.5 GHz. VSWR 1.25 Max. (RL.19dBMi wave ratio Frequency 1.5 to 3 GHz. VSWR 1.5 Max. (RL.14dBMi MECHANICAL CHARACTERISTICS Cable clamp strength (Against cable pull) Using a pulling tester, pull the cable axially at a rate (Against cable pull) of 10 mm/min. and record the strength at which	in) X -
wave ratio Frequency 1.5 to 3 GHz. VSWR 1.5 Max. (RL.14dBMi MECHANICAL CHARACTERISTICS Cable clamp strength (Against cable pull) Using a pulling tester, pull the cable axially at a rate (Against cable pull) of 10 mm/min. and record the strength at which	in) X -
MECHANICAL CHARACTERISTICS Cable clamp strength	in)
Cable clamp strength (Against cable pull) Using a pulling tester, pull the cable axially at a rate of 10 mm/min. and record the strength at which	v
(Against cable pull) of 10 mm/min. and record the strength at which	37
	3.7
the cable or connector breaks.	X -
Count Description of revisions Designed Checke	ed Date
A Description of total sons	
	IOMIVA 16 11 0
Remar <u>k</u> Approved NK.NIN	NOMIYA 16.11.08
	NOMIYA 16.11.08
NOTE 1 Measured in the condition that the conversion adaptor	
NOTE 1 Measured in the condition that the conversion adaptor (BNC(75)J-H.FLJ-BPA(40)) is mated with the connectors at both	AHASHI 16.11.08
NOTE 1 Measured in the condition that the conversion adaptor (BNC(75)J-H.FLJ-BPA(40)) is mated with the connectors at both ends of the harness. Checked NK.NIN Designed KS.TAKA	
NOTE 1 Measured in the condition that the conversion adaptor (BNC(75)J-H.FLJ-BPA(40)) is mated with the connectors at both ends of the harness. 2. Specifications are subject to change without notice. Checked NK.NIN Designed KS.TAKA	AHASHI 16 11 08
NOTE 1 Measured in the condition that the conversion adaptor (BNC(75)J-H.FLJ-BPA(40)) is mated with the connectors at both ends of the harness. 2. Specifications are subject to change without notice. Unless otherwise specified, refer to IEC 60512. Checked NK.NIN Designed KS.TAKA Drawn KS.TAKA	AHASHI 16.11.08
NOTE 1 Measured in the condition that the conversion adaptor (BNC(75)J-H.FLJ-BPA(40)) is mated with the connectors at both ends of the harness. 2. Specifications are subject to change without notice. Checked NK.NIN Designed KS.TAKA	AHASHI 16.11.0a
NOTE 1 Measured in the condition that the conversion adaptor (BNC(75)J-H.FLJ-BPA(40)) is mated with the connectors at both ends of the harness. 2. Specifications are subject to change without notice. Unless otherwise specified, refer to IEC 60512. Note QT:Qualification Test AT:Assurance Test X:Applicable Test Drawing No.	
NOTE 1 Measured in the condition that the conversion adaptor (BNC(75)J-H.FLJ-BPA(40)) is mated with the connectors at both ends of the harness. 2. Specifications are subject to change without notice. Unless otherwise specified, refer to IEC 60512. Note QT:Qualification Test AT:Assurance Test X:Applicable Test Drawing No. SPECIFICATION SHEET Part No. HEL75 21 PG	
NOTE 1 Measured in the condition that the conversion adaptor (BNC(75)J-H.FLJ-BPA(40)) is mated with the connectors at both ends of the harness. 2. Specifications are subject to change without notice. Unless otherwise specified, refer to IEC 60512. Note QT:Qualification Test AT:Assurance Test X:Applicable Test Drawing No.	